## **FOXSAT-HD**

## Satellite HD Digital Box





## FOXSAT-HD Satellite HD Digital Box

## Specification

System Resource

 Flash Memory
 16 Mbyte

 SDRAM
 256 Mbyte

 EEPROM
 8 Kbyte

Front-end

Tuner Type Satellite

Connector Type F-Type, IEC 169-24, Female

Demodulation [number of F/E set] 1, DVB-S2

Audio/Video Processing

Video Decoder [number] MPEG-2 MP@ML, MPEG4 HD HP@L3, PAL[1]

Audio Decoder [number] MPEG-1 Layer II, Dolby-AC3 Audio [1]

Front

Display 7 Segment

Buttons Power, TV/Radio, Vol-, Vol+, CH-, CH+,

OK, Guide, Menu

LED Standby on/off(Green/Red), TV(Green), Radio(Green)

Rear

SCART 1 TV, 1 VCR(RGB/YPbPr)

RF 1 Inpu

RCA 2 Set(1 Video, 2 Audio, 1 Component)

S/PDIF

HDMI HDCP version

Component Video Out 1 Set

USB Host version 1.1/2.0 LAN RJ-45 (Mac address)

Power cord Type Fixed

**Power Supply** 

Input Voltage AC 90-250V (Free voltage), SMPS

Power Consumption under 1Watt


**Physical Specification** 

Size (Width x Height x Depth) 280 x 45 x 200 mm

Weight(Net) 1.5 Kg

Accessory

RCU, Battery(AAAx2), Manual, Quick guide, Warranty Card, HDMI/RCA/SCART cable



 $\,\,$  Specifications and functions may be changed for improvement without notice in advance.

